PSR25-600-70 1/4



PRODUCT-DETAILS

PSR25-600-70 PSR25-600-70 Softstarter - 25 A - 208 ... 600 V AC



| General Information | |
|-------------------------|---|
| Global Commercial Alias | PSR25-600-70 |
| Extended Product Type | PSR25-600-70 |
| Product ID | 1SFA896108R7000 |
| ABB Type Designation | PSR25-600-70 |
| EAN | 7320500338285 |
| Catalog Description | PSR25-600-70 Softstarter - 25 A - 208 600 V AC |
| Long Description | The softstarter PSR25-600-70 has a rated maximum operational current of 25 A with an operating voltage span from 208600 V AC. The rated control voltage is between 100240 V AC at 50/60 Hz. PSR features a two-phase control soft start and stop through a voltage ramp. It has built-in bypass for easy installation and energy saving. A RUN and a TOR signal is available from a relay output in NO (normally open state). The start/stop ramp and time is easy to set by three potentiometers on the front. PSR is often used in combination with a manual motor starter (MMS) from ABB, so mechanical connection kits are available. Another popular option is Fieldbus communication, which can be enabled by an external adaptor and a Fieldbus plug. The PSR range is our most compact softstarters with basic functionality and values. They are suitable for small three-phase motors with nominal currents from 3105 A and can manage up to 100 starts per hour. Common applications |

Ordering

Minimum Order Quantity 1 piece

PSR25-600-70 2/4

Customs Tariff Number 85371091

| Popular Downloads | |
|--|--|
| Data Sheet, Technical Information | 1SFC132012C0201 |
| Instructions and Manuals | 1SFC132031M0001 |
| CAD Dimensional Drawing | 2CDC001079B0201 |
| Wiring Diagram | N/A |
| Willing Diagram | 1907 |
| Dimensions | _ |
| Product Net Width | 128 mm |
| Product Net Height | 160 mm |
| Product Net Depth / | 45 mm |
| Length Per deat Not Weight | 0.61 |
| Product Net Weight | 0.6 kg |
| Technical | |
| Rated Operational Voltage | 208 600 V AC |
| Rated Control Supply Voltage (U_s) | 100 240 V AC |
| Rated Control Circuit Voltage ($\mathrm{U_c}$) | 24 V DC |
| Rated Frequency (f) | 50/60 Hz Main Circuit 50 / 60 Hz |
| Rated Operational Power - In-Line Connection (Pe) | (230 V) 5.5 kW (400 V) 11 kW (500 V) 15 kW |
| Rated Operational Current - In-Line Connection (Ie) | 25 A |
| Service Factor Percentage | 100 % |
| Overload Protection | Recommended MS132 20 25 |
| Integrated Electronic Overload | No |
| Adjustable Rated Motor Current le | No |
| Starting Capacity at Maximum Rated Current le | 4xle for 6s |
| Ramp Time | 0 20 second [unit of time 1 10 second [unit of time |
| Initial Voltage During Start | 40 70 % |
| Step Down Voltage Special Ramp | 100 60 % |
| Current Limit Function | No |
| Switch for Inside Delta Connection | No |
| Run Signal Relay | Yes |
| By-pass Signal Relay | Yes |
| Fault Signal Relay | No. |
| Overload Signal Relay Signal Indication Completed Start Ramp | No. Green |
| (LED) Signal Indication Ready to Start/Standby ON (LED) | Green |
| Signal Indication Running R (LED) | Green |
| | 2004/07/06 |

PSR25-600-70 3/4

| Signal Indication Ramping Up/Down (LED) | Green |
|---|--|
| Number of Starts Per Hour | 10 |
| at 3.5*le for 7 sec. 50% ON Time 50% OFF Time | |
| Communication | FiledBusPlug(Optional) |
| Degree of Protection | IP20 |
| Terminal Type | Screw Terminals |
| Connecting Capacity Main Circuit | Rigid 1/2 x 2.5 10 mm² |
| Connecting Capacity | 1 x 0.75 2.5 |
| Control Circuit | 2 x 0.75 2.5 mm² Rigid 1 x 0.75 2.5 mm² Rigid 2 x 0.75 1.5 mm² |
| Connecting Capacity Supply Circuit | Rigid 1 x 0.75 2.5 mm ² |
| Tightening Torque | Control Circuit 0.6 N·m Main Circuit 2.3 N·m Supply Circuit 0.6 N·m |
| Product Main Type | PSR25 |
| Function | Soft start with voltage ramp Soft stop with voltage ramp |
| Technical UL/CSA | |
| Maximum Operating Voltage UL/CSA | Main Circuit 600 V |
| Tightening Torque UL/CSA | Control Circuit 5.3 in·lb Main Circuit 20.4 Supply Circuit 5.3 in·lb |
| Environmental Ambient Air Temperature Degree of Protection | Operation -25 +60 °C Storage -40 +70 °C IP20 |
| Material Compliance | |
| Conflict Minerals Reporting Template (CMRT) | 9AKK108467A5658 |
| REACH Declaration | 2CMT2022-006481 |
| RoHS Information | 2CMT2022-006500 |
| RoHS Status | Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019 |
| Toxic Substances Control Act - TSCA | 2CMT2023-006524 |
| WEEE B2C / B2B | Business To Business |
| WEEE Category | 5. Small Equipment (No External Dimension More Than 50 cm) |
| Certificates and Declarations | |
| CQC Certificate | CQC2006010304208086 |
| Declaration of Conformity - CCC | 2020980304001088 |
| Declaration of Conformity - CE | 1SFA1-90 |
| | |
| Container Information | |
| Package Level 1 Width | 137 mm |

PSR25-600-70 4/4

| Package Level 1 Depth / Length | 50 mm |
|---------------------------------|---------------|
| Package Level 1 Height | 176 mm |
| Package Level 1 Gross Weight | 0.7 kg |
| Package Level 1 EAN | 7320500338285 |
| Package Level 1 Units | box 1 piece |

| Classifications | |
|------------------------------------|-------------------------|
| Object Classification Code | Q |
| ETIM 7 | EC000640 - Soft starter |
| ETIM 8 | EC000640 - Soft starter |
| ETIM 9 | EC000640 - Soft starter |
| eClass | V11.0 : 27370907 |
| UNSPSC | 39121521 |
| IDEA Granular Category Code (IGCC) | 4740 >> Soft starter |

| Accessories | | | | |
|-----------------|---------------------------------|-----------------|----------|--------------------|
| Identifier | Description | Туре | Quantity | Unit Of Measure |
| 1SFA896212R1001 | PSR30-MS132 Connection Kit PSR3 | 80-MS132 | 1 | piece |
| 1SFA896312R1002 | PS-FBPA Fieldbus plug kit | PS-FBPA | 1 | piece |
| 1SFA896311R1001 | PSR-FAN3-45A FAN | SR-FAN3- 45A | 1 | piece |

Categories

 $Drives \rightarrow Softstarters \rightarrow Softstarters \rightarrow PSR \ Softstarters \rightarrow PSR25 \\ Low \ Voltage \ Products \ and \ Systems \rightarrow Control \ Products \rightarrow Softstarters \rightarrow PSR \ Softstarters \rightarrow PSR25$





