

PRODUCT-DETAILS

## PSR72-600-70

## PSR72-600-70 Softstarter - 72 A - 208 ... 600 V AC



| General Information     |  |
|-------------------------|--|
| Global Commercial Alias | PSR72-600-70   |
| Extended Product Type   | PSR72-600-70   |
| Product ID              | 1SFA896113R7000  |
| ABB Type Designation    | PSR72-600-70   |
| EAN                     | 7320500362617  |
| Catalog Description     | PSR72-600-70 Softstarter - 72 A - 208 600 V AC   |
| Long Description        | The softstarter PSR72-600-70 has a rated maximum operational current of 72 A with<br>an operating voltage span from 208600 V AC. The rated control voltage is between<br>100240 V AC at 50/60 Hz. PSR features a two-phase control soft start and stop<br>through a voltage ramp. It has built-in bypass for easy installation and energy saving. A<br>RUN and a TOR signal is available from a relay output in NO (normally open state). The<br>start/stop ramp and time is easy to set by three potentiometers on the front. PSR is<br>often used in combination with a manual motor starter (MMS) from ABB, so<br>mechanical connection kits are available. Another popular option is Fieldbus<br>communication, which can be enabled by an external adaptor and a Fieldbus plug. The<br>PSR range is our most compact softstarters with basic functionality and values. They<br>are suitable for small three-phase motors with nominal currents from 3105 A and can<br>manage up to 100 starts per hour. Common applications are, for example, pumps,<br>fans, compressors, and conveyors. |

2024/07/06

© 2024 ABB. All rights reserved.

| Ordering               |          |
|------------------------|----------|
| Minimum Order Quantity | 1 piece  |
| Customs Tariff Number  | 85371091 |

| Popular Downloads                    |                 |
|--------------------------------------|-----------------|
| Data Sheet, Technical<br>Information | 1SFC132012C0201 |
| Instructions and<br>Manuals          | 1SFC132033M000  |
| CAD Dimensional<br>Drawing           | 2CDC001079B0201 |
| Wiring Diagram                       | N/A             |
| Dimensions                           |                 |
| Product Net Width                    | 180 mm          |
| Product Net Height                   | 220 mm          |
| Product Net Depth /<br>Length        | 70 mm           |
| Product Net Weight                   | 2.1 kg          |
|                                      |                 |
| Technical                            |                 |
| Rated Operational<br>Voltage         | 208 600 V AC    |
| Rated Control Supply                 | 100 240 V AC    |

| Rated Control Supply      | 100 240 V AC               |
|---------------------------|----------------------------|
| Voltage (Us)              |                            |
| Rated Control Circuit     | 24 V DC                    |
| Voltage (U <sub>c</sub> ) |                            |
| Rated Frequency (f)       | 50/60 Hz                   |
|                           | Main Circuit 50 / 60 Hz    |
| Rated Operational Power   | (230 V) 22 kW              |
| - In-Line Connection (Pe) | (400 V) 37 kW              |
|                           | (500 V) 45 kW              |
| Rated Operational         | 72 A                       |
| Current - In-Line         |                            |
| Connection (le)           |                            |
| Service Factor            | 100 %                      |
| Percentage                |                            |
| Overload Protection       | Recommended MS495 57 75    |
| Integrated Electronic     | No                         |
| Overload                  |                            |
| Adjustable Rated Motor    | No                         |
| Current le                |                            |
| Starting Capacity at      | 4xle for 6s                |
| Maximum Rated Current     |                            |
| le                        |                            |
| Ramp Time                 | 0 20 second [unit of time] |
|                           | 1 10 second [unit of time] |
| Initial Voltage During    | 40 70 %                    |
| Start                     |                            |
| Step Down Voltage         | 100 60 %                   |
| Special Ramp              |                            |
| Current Limit Function    | No                         |
| Switch for Inside Delta   | No                         |
| Connection                |                            |
|                           |                            |

© 2024 ABB. All rights reserved.

| Run Signal Relay   | Yes  |
|--|--|
| By-pass Signal Relay   | Yes  |
| Fault Signal Relay   | <u> </u>   |
| Overload Signal Relay Signal Indication  | Green  |
| Completed Start Ramp<br>(LED)  | Green  |
| Signal Indication Ready<br>to Start/Standby ON<br>(LED)                          | Green  |
| Signal Indication<br>Running R (LED)   | Green  |
| Signal Indication<br>Ramping Up/Down<br>(LED)                                    | Green  |
| Number of Starts Per<br>Hour at 3.5*1e for 7 sec.<br>50% ON Time 50% OFF<br>Time | 10   |
| Communication  | FiledBusPlug(Optional)   |
| Degree of Protection   | IP10   |
| Terminal Type  | Main Circuit: Bars   |
| Connecting Capacity<br>Main Circuit  | Rigid 1x 10 95 mm²<br>Rigid 2 x 6 35 mm²   |
| Connecting Capacity<br>Control Circuit   | 1 x 0.75 2.5<br>2 x 0.75 2.5 mm²<br>Rigid 1 x 0.75 2.5 mm²<br>Rigid 2 x 0.75 1.5 mm² |
| Connecting Capacity<br>Supply Circuit  | Rigid 1 x 0.75 2.5 mm²   |
| Tightening Torque  | Control Circuit 0.6 N·m<br>Main Circuit 8 N·m<br>Supply Circuit 0.6 N·m              |
| Product Main Type  | PSR72  |
| Function   | Soft start with voltage ramp<br>Soft stop with voltage ramp                          |
| Technical UL/CSA   |  |
| Maximum Operating<br>Voltage UL/CSA  | Main Circuit 600 V   |
| Tightening Torque  | Control Circuit 5.3 in·lb  |
| UL/CSA   | Main Circuit 70.8<br>Supply Circuit 5.3 in-Ib  |
| Environmental  |  |
| Ambient Air  | Operation -25 +60 °C   |
| Temperature  | Storage -40 +70 °C   |
| Degree of Protection   | IP10   |
| Material Compliance  |  |
| Conflict Minerals<br>Reporting Template  | 9AKK108467A5658  |
| (CMRT)   |  |
| REACH Declaration  | 2CMT2022-006481  |
| RoHS Information   | 2CMT2022-006500  |

© 2024 ABB. All rights reserved.

2024/07/06

Subject to change without notice

| RoHS Status        | Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019 |
|--------------------|--|
| Toxic Substances   | 2CMT2023-006524  |
| Control Act - TSCA |  |
| WEEE B2C / B2B     | Business To Business   |
| WEEE Category      | 5. Small Equipment (No External Dimension More Than 50 cm)             |

| CQC Certificate   | CQC2008010304295498 |
|---|---------------------|
| Declaration of<br>Conformity - CCC  | 2020980304001090    |
| Declaration of<br>Conformity - CE   | 1SFA1-9!            |
| Container Information   |                     |
|   | 195 mr              |
| Container Information<br>Package Level 1 Width<br>Package Level 1 Depth /<br>Length                           | 195 mn<br>86 mn     |
| Package Level 1 Width<br>Package Level 1 Depth /  |                     |
| Package Level 1 Width<br>Package Level 1 Depth /<br>Length  | 86 mn               |
| Package Level 1 Width<br>Package Level 1 Depth /<br>Length<br>Package Level 1 Height<br>Package Level 1 Gross | 86 mn<br>230 mn     |

| Classifications                       |                         |
|---------------------------------------|-------------------------|
| Object Classification<br>Code         | Q                       |
| ETIM 7                                | EC000640 - Soft starter |
| ETIM 8                                | EC000640 - Soft starter |
| ETIM 9                                | EC000640 - Soft starter |
| eClass                                | V11.0 : 27370907        |
| UNSPSC                                | 39121521                |
| IDEA Granular Category<br>Code (IGCC) | 4740 >> Soft starter    |

| Accessories     |                              |                    |        |                    |
|-----------------|------------------------------|--------------------|--------|--------------------|
| Identifier      | Description Type Quantity    |                    | antity | Unit Of<br>Measure |
| 1SFA899002R1072 | PSLW-72 Terminal Enlargement | PSLW-72            | 1      | piece              |
| 1SFA896312R1002 | PS-FBPA Fieldbus plug kit    | PS-FBPA            | 1      | piece              |
| 1SFA896313R1001 | PSR-FAN60-105A FAN           | PSR-FAN60-<br>105A | 1      | piece              |

4/5

## Categories

 $\mathsf{Drives} \to \mathsf{Softstarters} \to \mathsf{Softstarters} \to \mathsf{PSR}\,\mathsf{Softstarters} \to \mathsf{PSR72}$ 

 $\text{Low Voltage Products and Systems} \rightarrow \text{Control Products} \rightarrow \text{Softstarters} \rightarrow \text{Softstarters} \rightarrow \text{PSR Softstarters} \rightarrow \text{PSR72}$ 





